

**To configure a password for privileged mode on Router2:**

```
Paris(config)# enable secret class
```

```
Paris(config)#
```

**To configure a password for console port on Router2:**

```
Paris(config)# line console 0
```

```
Paris(config-line)# password cisco
```

```
Paris(config-line)# login
```

```
Paris(config-line)# exit
```

```
Paris(config)#
```

**To enable remote access (vty) on Router2:**

```
Paris(config-line)# line vty 0 4
```

```
Paris(config-line)# password 12345678
```

```
Paris(config-line)# login
```

```
Paris(config-line)# exit
```

```
Paris(config)#
```

**Step 3: Configure Serial interface 0/0/0 on Router1**

From the global configuration mode, configure interface Serial 0/0/0 on Router1. Refer to the interface chart.

```
London(config)# interface serial 0/0/0
```

```
London(config-if)# ip address 192.168.2.1 255.255.255.252
```

```
London(config-if)# clock rate 64000
```

```
London(config-if)# no shutdown
```

```
London(config-if)# exit
```