

Cadence Tutorial 7

Generating HSPICE Netlist from Schematic

EE577b Spring2000

In this tutorial, I will show how to generate HSPICE netlist from schematic.

1. Tutorial Setup


Tutorial 1,2,4 are necessary to start this tutorial.

2. Open adder8 Schematic

As usual!!

3. Initiate Netlist Generation Tool

1. sch:Tools->Other
2. sch:Simulation->Initialize
Initialize Environment form will be displayed.



3. Type *hspice.run1* or use default (*spice.run1*) in **Simulation Run Directory**
4. Click OK.

Initialize Environment form will be displayed.



5. Choose *hspice* for **Simulator Name**
6. Use default for others.
7. Click OK.